



SIDE VIEW

FRONT VIEW

- DIMENSION "A" 11" MINIMUM - 15" MAXIMUM
- DIMENSION "B" 9" MINIMUM TO EDGE OF ACCESS OPENING.
- DIMENSION "C" 10" MINIMUM TO EDGE OF ACCESS OPENING.
- DIMENSION "D" 8" MINIMUM FROM METER CENTERLINE TO TOP OF ANY PROTRUDING SWITCH OR BREAKER OR TO BOTTOM OF THE ENCLOSING CABINET.

ALL DIMENSIONS SHOWN ARE IN INCHES

NOTES:

1. CARE SHOULD BE EXERCISED TO DESIGN CABINET SUCH THAT NEITHER THE ROOF NOR DOOR SUPPORTS WILL INTERFERE WITH INSTALLATION OF THE METER.
2. COMPLY WITH EUSERC MANUAL SECTION "G", DRAWING "G6" LATEST REVISION.

					BURBANK WATER AND POWER – ELECTRIC SERVICES	
					INSTALLATION GUIDE METER CABINET ENCLOSURE CLEARANCES 0-600 VOLTS	
						DRAWING No.
						S-831A
						Sheet 1 of 1
A	NEW DRAWING	MEP HAM	SK	7/10/24		
No.	REVISIONS	BY	APPR'V'D	DATE		